

The Consolidated Edison Commercial and Industrial (C&I) Energy Efficiency Program Prescriptive Interior & Exterior Lighting Guide

V. 1.0

Effective: September 13, 2022

This guide and the content herein serve as a reference to the requirements set forth as part of the Consolidated Edison Commercial and Industrial (C&I) Energy Efficiency Program Manual. Since the Program Manual may be amended, this guide defers to any changes made to the Con Edison C&I Energy Efficiency Program Manual until such time this guide is updated.

Table of Contents

- 1.0 General Requirements: 3
- 2.0 Incentives: 4
- 3.0 Eligibility and Baselines: 5
 - New Fixture Replacement Types 5
 - 1. LED Exit Sign 5
 - 2. Direct Linear Ambient Luminaires 5
 - 3. Linear Ambient Luminaires with Indirect Component 6
 - 4. Parking Garage/Fuel Canopy Luminaires 7
 - 5. Outdoor Pole/ Arm-Mounted Luminaires 8
 - 6. Downlights with Screw-In or Pin-Based Lamps 8
 - 7. Bollards/Landscape/Accent Flood and Spot Luminaires 9
 - 8. Track or Mono-Point Luminaires 9
 - 9. High Bay/Low Bay Luminaires 10
 - 10. 1x4 Luminaires for Ambient Lighting 11
 - 11. 2x2 Luminaires for Ambient Lighting 12
 - 12. 2x4 Luminaires for Ambient Lighting 14
 - 13. Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires 15
 - Retrofit Replacement Types 15
 - 14. Direct Linear Ambient Luminaires 15
 - 15. Ambient Luminaires with Indirect Component 16
 - 16. Replacement Luminaire Category: Outdoor Pole/ Arm Mounted Luminaires 16
 - 17. Downlights with Screw-In or Pin-Based Lamps 17
 - 18. High Bay/Low Bay Luminaires 17
 - 19. 1x4 Luminaires for Ambient Lighting 18
 - 20. 2x2 Luminaires for Ambient Lighting 18
 - 21. 2x4 Luminaires for Ambient Lighting 18
 - 22. Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires 19
- 4.0 Examples 20
- 5.0 Frequently Asked Questions 21

1.0 General Requirements:

All prescriptive solid state lighting fixture and retrofit kit projects whose completed application packages are submitted on or after September 13, 2022 are subject to the lighting incentive rates and eligibility requirements described herein.

- Eligibility is based on minimum wattage reduction instead of one-for-one replacement of existing fixture type. Wattage reduction is calculated using the following standardized baseline wattages for the existing luminaire type installed. Wattage reduction is **NOT** calculated based on existing fixture wattage.
- Upgrading and/or replacing existing LED lamps/fixtures are not eligible for incentives.
- De-lamping is not eligible for incentives.
- Fixtures and retrofit kits, excluding LED exit signs and downlights, must be solid-state lighting certified and listed on the Design Lights Consortium (DLC) Qualified Product List (QPL) version 5.1 or later at the time of application to be eligible for the program.
- LED exit signs and downlights must be ENERGY STAR listed.
- DLC or ENERGY STAR screenshots **must** be submitted to Con Edison as part of the project application package.
- When submitting equipment specifications, please highlight all information relevant to your project, for example, equipment model numbers, wattage, etc. Doing so will help ensure a more efficient review process.
- Projects that trigger energy code and exceed code requirements are eligible for lighting incentive via lighting power density method. Note that prescriptive lighting incentives are **NOT** offered to projects that trigger the energy code.

Lighting Replacement Measures not listed below are presently **NOT** eligible for incentives under the Con Edison C&I Program.

2.0 Incentives:

The following are the prescriptive incentives currently offered for LED interior and exterior lighting measures:

- Incentives are based on the DLC category of the product installed.
- There is one incentive price for each type of proposed fixture or retrofit replacement

Replacement Type	Rated Source	Replacement Luminaire Category	Incentive
Fixture	Energy Star	LED Exit Sign	\$20
	DLC	Direct Linear Ambient Luminaires	\$80
	DLC	Linear Ambient Luminaires with Indirect Component	\$80
	DLC	Parking Garage/Fuel Canopy Luminaires	\$180
	DLC	Outdoor Pole/Arm-Mounted Luminaires	\$150
	Energy Star	Downlights w. Screw-In or Pin-Based Lamps	\$40
	DLC	Bollards/Landscape/Accent Flood and Spot Luminaires	\$100
	DLC	Track or Mono-Point Luminaires	\$40
	DLC	High Bay/Low Bay Luminaires	\$140
	DLC	1x4 Luminaires for Ambient Lighting	\$40
	DLC	2x2 Luminaires for Ambient Lighting	\$40
	DLC	2x4 Luminaires for Ambient Lighting	\$80
	DLC	Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires	\$150
Retrofit	DLC	Direct Linear Ambient Luminaires	\$40
	DLC	Linear Ambient Luminaires with Indirect Component	\$40
	DLC	Outdoor Pole/Arm-Mounted Luminaires	\$150
	Energy Star	Downlights w. Screw-In or Pin-Based Lamps	\$20
	DLC	High Bay/Low Bay Luminaires	\$70
	DLC	1x4 Luminaires for Ambient Lighting	\$20
	DLC	2x2 Luminaires for Ambient Lighting	\$20
	DLC	2x4 Luminaires for Ambient Lighting	\$40
	DLC	Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires	\$150

3.0 Eligibility and Baselines:

Wattage reduction is calculated using the following standardized baseline wattages for the existing luminaire type installed. Wattage reduction is **NOT** calculated based on existing fixture wattage. This section reviews the various eligible fixture replacement and retrofit kit measures, wattage reduction criteria, and baseline selection.

New Fixture Replacement Types

1. LED Exit Sign

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	Energy Star	LED Exit Sign	5

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Exit Sign	Incandescent or CFL Exit Sign	11

2. Direct Linear Ambient Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Direct Linear Ambient Luminaires	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
Screw or Pin Based Incandescent	Incandescent Fixture ≤60W	37.5
	Incandescent Fixture >60W	116

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture ≤32W	37.5
	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 1-2 Lamp	60
	CFL Long – Biaxial 3-4 Lamp	150
Track or Mono Point	Incandescent Track or Mono Point Luminaires	37.5
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
T8 High Bay - 8 Lamp Fluorescent Fixture	304	
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

3. Linear Ambient Luminaires with Indirect Component

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Linear Ambient Luminaires with Indirect Component	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5

Existing Luminaire Category	Luminaire Type	Baseline Wattage
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Screw or Pin Based Incandescent	Incandescent Fixture ≤60W	37.5
	Incandescent Fixture >60W	116
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture ≤32W	37.5
	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 1-2 Lamp	60
	CFL Long – Biaxial 3-4 Lamp	150
Track or Mono Point	Incandescent Track or Mono Point Luminaires	37.5
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
	T8 High Bay - 8 Lamp Fluorescent Fixture	304
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

4. Parking Garage/Fuel Canopy Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Parking Garage / Fuel Canopy Luminaires	80

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Parking Garage/Fuel Canopy Luminaires	HID Parking Garage Fixture ≤100W	95
	HID Parking Garage Fixture 101W to 249W	215
	HID Parking Garage Fixture ≥250W	295
High Bay / Low Bay Luminaires	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
	T8 High Bay - 8 Lamp Fluorescent Fixture	304
Troffers	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

5. Outdoor Pole/ Arm-Mounted Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Outdoor Pole / Arm-Mounted Luminaires	150

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Outdoor Pole Mounted Luminaires	HID Pole Fixture 101W to 249W	215
	HID Pole Fixture 250W to 399W	295
	HID Pole Fixture 400W to 999W	457
	HID Pole Fixture ≥1000W	1150

6. Downlights with Screw-In or Pin-Based Lamps

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	Energy Star	Downlights with Screw-In or Pin Based Lamps	60

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Screw or Pin Based Incandescent	Incandescent Fixture >60W	116
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 3-4 Lamp	150
Troffers	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

7. Bollards/Landscape/Accent Flood and Spot Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Bollards/Landscape/Accent Flood and Spot Luminaires	100

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
	HID Exterior Fixture 101 - 249 Watts	215
	HID Exterior Fixture ≥ 250 Watts	295

8. Track or Mono-Point Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Track or Mono-Point Luminaires	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Screw or Pin Based Incandescent	Incandescent Fixture ≤60W	37.5
	Incandescent Fixture >60W	116
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture ≤32W	37.5
	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 1-2 Lamp	60
	CFL Long – Biaxial 3-4 Lamp	150
Track or Mono Point	Incandescent Track or Mono Point Luminaires	37.5
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

9. High Bay/Low Bay Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	High Bay / Low Bay Luminaires	100

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 2-Lamp Fluorescent Fixture	136

Existing Luminaire Category	Luminaire Type	Baseline Wattage
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
High Intensity Discharge (HID) Exterior Fixtures	HID Exterior Fixture 101 - 249 Watts	215
	HID Exterior Fixture ≥ 250 Watts	295
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
T8 High Bay - 8 Lamp Fluorescent Fixture	304	

10. 1x4 Luminaires for Ambient Lighting

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	1x4 Luminaires for Ambient Lighting	15

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 1-Lamp Fluorescent Fixture	17
	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Screw or Pin Based Incandescent	Incandescent Fixture ≤60W	37.5
	Incandescent Fixture >60W	116
	CFL Fixture ≤32W	37.5

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 1-2 Lamp	60
	CFL Long – Biaxial 3-4 Lamp	150
Track or Mono Point	Incandescent Track or Mono Point Luminaires	37.5
High Intensity Discharge (HID) Exterior Fixtures	HID Exterior Fixture ≤100W	95
	HID Exterior Fixture 101 - 249 Watts	215
	HID Exterior Fixture ≥ 250 Watts	295
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
	T8 High Bay - 8 Lamp Fluorescent Fixture	304
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

11. 2x2 Luminaires for Ambient Lighting

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	2x2 Luminaires for Ambient Lighting	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5

Commercial and Industrial Energy Efficiency Program Prescriptive Interior & Exterior Lighting Guide

Existing Luminaire Category	Luminaire Type	Baseline Wattage
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Screw or Pin Based Incandescent	Incandescent Fixture ≤60W	37.5
	Incandescent Fixture >60W	116
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture ≤32W	37.5
	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 1-2 Lamp	60
	CFL Long – Biaxial 3-4 Lamp	150
Track or Mono Point	Incandescent Track or Mono Point Luminaires	37.5
High Intensity Discharge (HID) Exterior Fixtures	HID Exterior Fixture ≤100W	95
	HID Exterior Fixture 101 - 249 Watts	215
	HID Exterior Fixture ≥ 250 Watts	295
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
	T8 High Bay - 8 Lamp Fluorescent Fixture	304
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

12. 2x4 Luminaires for Ambient Lighting

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	2x4 Luminaires for Ambient Lighting	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272
Screw or Pin Based Incandescent	Incandescent Fixture ≤60W	37.5
	Incandescent Fixture >60W	116
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture ≤32W	37.5
	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 1-2 Lamp	60
	CFL Long – Biaxial 3-4 Lamp	150
High Intensity Discharge (HID) Exterior Fixtures	HID Exterior Fixture ≤100W	95
	HID Exterior Fixture 101 - 249 Watts	215
	HID Exterior Fixture ≥ 250 Watts	295
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
	T8 High Bay - 8 Lamp Fluorescent Fixture	304

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

13. Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Fixture	DLC	Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires	150

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Wall Packs	HID Exterior Wall Pack Fixture 101W to 399W	242
	HID Exterior Wall Pack Fixture ≥400W	455

Retrofit Replacement Types

14. Direct Linear Ambient Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	Direct Linear Ambient Luminaires	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68

Existing Luminaire Category	Luminaire Type	Baseline Wattage
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272

15. Ambient Luminaires with Indirect Component

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	Linear Ambient Luminaires with Indirect Component	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Linear Ambient Luminaires	2 Foot 2-Lamp Fluorescent Fixture	36
	2 Foot 3-Lamp Fluorescent Fixture	55
	2 Foot 4-Lamp Fluorescent Fixture	74
	4 Foot 1-Lamp Fluorescent Fixture	29.5
	4 Foot 2-Lamp Fluorescent Fixture	57
	4 Foot 3-Lamp Fluorescent Fixture	84.5
	4 Foot 4-Lamp Fluorescent Fixture	112
	8 Foot 1-Lamp Fluorescent Fixture	68
	8 Foot 2-Lamp Fluorescent Fixture	136
	8 Foot 3-Lamp Fluorescent Fixture	204
	8 Foot 4-Lamp Fluorescent Fixture	272

16. Replacement Luminaire Category: Outdoor Pole/ Arm Mounted Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	Outdoor Pole / Arm-Mounted Luminaires	150

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
	HID Pole Fixture 101W to 249W	215
	HID Pole Fixture 250W to 399W	295
	HID Pole Fixture 400W to 999W	457
	HID Pole Fixture ≥1000W	1150

17. Downlights with Screw-In or Pin-Based Lamps

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	Downlights with Screw-In or Pin Based Lamps	60

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Screw or Pin Based Incandescent	Incandescent Fixture >60W	116
Screw or Pin Based Compact Fluorescent Lights (CFLs)	CFL Fixture >32W	116
	CFL Short - 1-2 Lamp	65
	CFL Short - 3-4 Lamp	90
	CFL Long – Biaxial 3-4 Lamp	150

18. High Bay/Low Bay Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	High Bay / Low Bay Luminaires	100

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
High Bay / Low Bay Luminaires	HID Interior Fixture <250W	215
	HID Interior Fixture 250W to 399W	295
	HID Interior Fixture 400W to 999W	457
	HID Interior Fixture ≥1000W	1150
	T5 High Bay - 2 Lamp Fluorescent Fixture	117
	T5 High Bay - 3 Lamp Fluorescent Fixture	179
	T5 High Bay - 4 Lamp Fluorescent Fixture	234
	T8 High Bay - 4 Lamp Fluorescent Fixture	152
	T8 High Bay - 6 Lamp Fluorescent Fixture	226
	T8 High Bay - 8 Lamp Fluorescent Fixture	304

20. 1x4 Luminaires for Ambient Lighting

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	1x4 Luminaires for Ambient Lighting	15

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58

21. 2x2 Luminaires for Ambient Lighting

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	2x2 Luminaires for Ambient Lighting	20

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Troffers	2x2 Troffer - 2 Lamp Fluorescent Fixture	70

22. 2x4 Luminaires for Ambient Lighting

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	2x4 Luminaires for Ambient Lighting	30

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Troffers	1x4 Troffer - 1 Lamp Fluorescent Fixture	37
	1x4 Troffer - 2 Lamp Fluorescent Fixture	58
	2x2 Troffer - 2 Lamp Fluorescent Fixture	70
	2x4 Troffer - 2 Lamp Fluorescent Fixture	71
	2x4 Troffer - 3 Lamp Fluorescent Fixture	84
	2x4 Troffer - 4 Lamp Fluorescent Fixture	113

23. Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires

Replacement Type	Rated Source	Proposed Luminaire Category	Minimum Wattage Reduction
Retrofit	DLC	Outdoor Full-Cutoff/Non-Cutoff/Semi-Cutoff Wall-Mounted Luminaires	150

Baseline from which Minimum Wattage Reduction is Calculated

Existing Luminaire Category	Luminaire Type	Baseline Wattage
Wall Packs	HID Exterior Wall Pack Fixture 101W to 399W	242
	HID Exterior Wall Pack Fixture ≥400W	455

4.0 Eligibility Examples

Type of Equipment to be Replaced / Retrofitted	Replacement Category	Quantity of Equipment Being Replaced	Actual Wattage of Equipment Being Replaced	Baseline Wattage ¹	New Equipment Being Installed	Quantity of New Equipment	Wattage of New Equipment	Wattage Reduction ²	Minimum Wattage Reduction Based on New Equipment	Eligible for Incentives?	Incentive Rate ³	Incentive
4 Foot 2-Lamp Fluorescent Fixture Replacement	Fixture Replacement	100	72	57	4 Foot Direct Linear Ambient Luminaires	100	44	57 – 44 = 13	20	Not Eligible	N/A	
2x2 Troffer - 2 Lamp Fluorescent Fixture Replacement	Retrofit Kit	40	80	70	2x2 Luminaires for Ambient Lighting	40	23	70 – 23 = 47	20	Eligible	\$20/Fixture	40 x \$20 = \$800
2x4 Troffer - 4 Lamp Fluorescent Fixture Replacement	Fixture Replacement	25	128	113	2x2 Luminaires for Ambient Lighting	50	40	113 – 40 = 73	20	Eligible	\$40/Fixture	50 x \$40 = \$2,000
Incandescent Fixture >60W Replacement	Fixture Replacement	14	75	116	Energy Star Downlights	40	15	116 – 15 = 111	60	Not Eligible ³	N/A	

¹ Baseline wattages should be selected from Section 3.0 above

² Wattage Reduction = Baseline Wattage – Wattage of New Equipment

³ Incentive rates are based on proposed fixture/retrofit to be installed

⁴ Projects with an existing fixture quantity that does not equal the proposed quantity would be evaluated by Con Edison on a case-by-case basis to determine whether energy code is triggered. If energy code is triggered and code requirements exceeded, the project would then be eligible for lighting incentives under the Lighting Power Density (LPD) method (and not eligible for prescriptive lighting incentives).

5.0 Frequently Asked Questions

1. **Question:** Are lighting incentive rates based on existing fixtures being replaced/retrofitted or on proposed equipment?

Answer: Lighting incentives are based on the proposed fixture replacement/retrofit category and quantity.

2. **Question:** When do the new lighting incentives and eligibility criteria take effect? Will new incentive rates be retroactively applied to projects already submitted to the Commercial & Industrial Program?

Answer: All new projects with completed application packages submitted on or after September 13, 2022 are subject to the incentive rates and eligibility criteria described in this document.

Applicants have until September 6th at 5PM EST to submit new lighting projects and existing lighting projects will be grandfathered into the C&I one-for-one lighting eligibility criteria and incentive rates. The C&I Program will stop accepting lighting projects on September 6th at 5PM EST, a few days before launch of new lighting incentives. Lighting projects submitted before 5PM on September 6th will be accepted using either the Electric Measure Tool version 22.0 or through Incentive Navigator.

The C&I Program will resume accepting lighting projects on September 13th. Note that projects submitted on or after September 13th will be subject to the new prescriptive requirements and incentive rates. These projects shall use the Con Edison C&I Lighting Calculator. The Lighting Calculator can be downloaded directly from the C&I program website. Lighting projects submitted with the Electric Measure Tool version 22.0 will not be eligible for incentives.

3. **Question:** What happens if I miss the 5PM EST September 6th deadline to submit my one-for-one lighting project on?

No lighting projects will be accepted after 5PM EST on September 6th. The C&I Program will resume accepting lighting projects on September 13th.

4. **Question:** How do we calculate energy savings and determine eligibility for new lighting projects?

Answer: Applicants should use the C&I Lighting Calculator to determine eligibility of fixture replacements and/or retrofits as well as calculate energy savings and incentives. This calculator is excel-based and can be downloaded directly from the C&I program website. This Lighting Calculator supersedes the following lighting tabs on the C&I Electric Measure Tool:

- One-for-one replacement
- Interior Lighting Control
- Bi-Level Lighting Control
- Gut Renovations – LPD
- Gut Renovations – Networked Controls

5. **Question:** I've already completed the Electric Measure Tool version 22.0 lighting tabs; can I submit for incentives after launch of the new lighting offering?

Answer: No, lighting projects submitted after the launch of the new lighting incentives must use the C&I Lighting Calculator. Lighting projects submitted with the Electric Measure Tool will be rejected and sent back to the applicant for revision to the new Lighting Calculator. The Lighting Calculator can be downloaded directly from the C&I program website.

6. **Question:** Should minimum wattage reduction be calculated based on existing fixture wattage?

Answer: No, minimum wattage reduction is calculated using standardized program baseline wattages for the existing fixture type installed. Wattage reduction calculations do not consider the existing fixture wattage.

7. **Question:** Based on the standardized program baseline wattage specified for my existing equipment type and my new equipment wattage, I do not meet the program's minimum wattage reduction requirements. However, my existing equipment wattage is much higher than the standardized program baseline wattage. Can I use my existing equipment wattage for the purposes of eligibility?

Answer: No, eligibility is based on wattage reduction calculated using standardized program baseline wattages for the existing fixture type installed. Wattage reduction calculations do not consider the existing fixture wattage.

8. **Question:** Is de-lamping eligible for incentives? Does a LED proposed measure replacing a LED existing qualify for incentives?

Answer: De-lamping and LED to LED replacement will not be eligible and will not qualify for an incentive through the C&I Energy Efficiency Program.

9. **Question:** Are gut renovation projects or projects triggering code eligible for prescriptive lighting incentives?

Answer: Gut Renovations and projects that trigger energy code are eligible for lighting incentives via lighting power density (LPD) method. Refer to the Con Edison Commercial and Industrial Energy Efficiency Program Manual for more information on LPD incentives. Prescriptive lighting incentives are NOT offered to projects that trigger the energy code.

10. **Question:** Are there any changes to bi-level or lighting control incentives as part of this new lighting offering?

Answer: No, there are no changes to Commercial & Industrial bi-level lighting or lighting control incentives currently.